

## B11 Torpedo tip E12 or E26 Base





## **Key Features & Benefits**

The new 12V E12 or E26 **B11 (torpedo tip)** LED series integrates a set of filament LED sources and is ideal to replace **incandescent** bulbs. Available: 2W and 4W options. This series LED light bulbs are highly versatile, which can be in outdoor enclosed fixtures and offer significant energy savings and environmentally friendly. Light output is 360° which is perfect for even dispersion applications.

## **Technical Specifications:**

Model Name	JQ-DCE12-A02K27	JQ-DCE12-A04K27	JQ-DCE26-A04K27
Photo			
Halogen Replacement	20 Watt	40 Watt	40 Watt
Operating Voltage:	12 AC/DC	12 AC/DC	12 AC/DC
Power consumption:	2 Watt	4 Watt	4 Watt
Dimmable: *	Yes	Yes	Yes
Dimensions:	2.95" x 1.38"D	2.95" x 1.38"D	2.95" x 1.38"D
CRI:	> 80	>80	>80
CCT Option:	2700K	2700K	2700K
Luminous Flux:	100 lm.	200 lm.	200 lm.
Operating	-20° C - +50° C	-20° C - +50° C	-20° C - +50° C
Temperature:			
Storage Temperature	-30° C - +60° C	-30° C - +60° C	-30° C - +60° C
Safety Certification:	FCC Compliance	FCC Compliance	FCC Compliance
Rated Lifespan:	>25,000hrs.	>25,000hrs.	>25,000hrs.

**Notes**: Wattage +/- 10% ; Lumen Values +/- 5Lms. CRI +/- 5% ; Dimmable\* fully tested with LUTRON© DVEL magnetic low voltage dimmer or electrical dimmer with minimum load

JQ Green America Inc.